

True Circular Polarization

Handles 25 kW per Bay

Multiplexes over 6 MHz Bandwidth

Shively Standard Features:

- Ring Stub Design
- Consistently Predictable Patterns
- Digital-Ready
- Pattern Studies Available
- No Factory Personnel Needed to Install
- Adjustable Fine-Matching Transformer
- Radomes and Deicers Available
- Rugged Corrosion-Resistant Mounts
- Works with Regular Towers; No Need for Special Frequency-Sensitive Tower Sections
- Pressure Relief Valve for Easy Purging of the System
- Special Spacing, H/V Ratios, Null Fill and Beam Tilt Avail



Performance Specifications:

Polarization: Right circular.

VSWR: 1.05 : 1 ± 200 kHz for a single-frequency antenna

1.1 : 1 over ± 200 KHz for a dual frequency antenna with up to 6 MHz frequency separation.

Azimuth Pattern Circularity: Horizontal component ± 1.5 dB on pole.

Input Connection: Female 4-1/16 in flange, except for 2-bay antenna: 3-1/8 in EIA.

Electrical Specifications:

No. of Bays	Gain		Power Rating kW	No. of Bays	Gain		Power Rating kW
	Power	dB			Power	dB	
2	0.70	-1.54	50	8	2.53	4.03	80
3	1.01	1.05	75	10	3.14	4.96	80
4	1.31	1.17	80	12	3.75	5.24	80
5	1.62	2.08	80	14	4.35	6.39	80
6	1.92	2.83	80	16	4.96	6.96	80
7	2.22	3.47	80				

Notes:

1. Our gain figures are derived from the computed directivity and include the losses in the antenna feed system.

Gain is provided for one polarization and is equal in circularly polarized antennas for both horizontal and vertical components.

Gain will be reduced if null fill, beam tilt, special H/V ratio, or special wavelength spacing is provided. Gain will increase in a directional array by the directivity of the azimuth pattern.

Document No. ds-6814-hw (0701)

A Division of Howell Laboratories, Inc., P. O. Box 389, Bridgton, Maine 04009 USA

(207) 647-3327

1-888-SHIVELY

Fax: (207)647-8273

An Employee-Owned Company

www.shively.com

sales@shively.com

Certified to ISO-9001:2000

Model 6814 Size and Weight (Half-Wave-Spaced):

No. of Bays	Vertical Tower Space						Weight					
	Antenna Radiation Aperture		Physical Space Used		Total Tower Space Recommended		Without radomes		With radomes		With radomes & 1/2" (1.2 cm) radial ice	
	ft	m	ft	m	ft	m	lb	N	lb	N	lb	N
2	5	1.6	14	4.6	25	8.2	228	1017	368	1641	901	4018
3	10	3.3	19	6.2	30	9.8	320	1427	530	2364	1348	6012
4	15	4.9	24	7.9	35	11.5	412	1838	692	3086	1795	8006
5	20	6.6	29	9.5	40	13.1	504	2248	854	3809	2243	10004
6	25	8.2	34	11.2	45	14.8	597	2663	1017	4536	2690	11997
7	30	9.8	39	12.8	50	16.4	689	3073	1179	5258	3136	13987
8	35	11.5	38	12.5	55	18.0	772	3443	1332	5941	3553	15846
10	45	14.8	48	15.7	65	21.3	935	4170	1635	7292	4412	19678
12	55	18.0	58	19.0	75	24.6	1120	4995	1960	8742	5306	23665
14	65	21.3	68	22.3	85	27.9	1304	5816	2284	10187	6200	27652
16	75	24.6	78	25.6	95	31.2	1488	6636	2608	11632	7095	31644

Windload (Half-Wave-Spaced):

No. of Bays	Revision 'C'						Revision 'F'					
	Without radomes		With radomes		With radomes & 1/2" (1.2 cm) radial ice		Without radomes		With radomes		With radomes & 1/2" (1.2 cm) radial ice	
	lb	N	lb	N	lb	N	(ft ²)	m ²	(ft ²)	m ²	(ft ²)	m ²
2	284	1267	1103	4919	1166	5200	9.2	0.9	28.5	2.6	30.5	2.8
3	454	2025	1684	7511	1786	7966	14.8	1.4	43.8	4.1	47.1	4.4
4	625	2788	2265	10102	2406	10731	20.5	1.9	59.0	5.5	63.7	5.9
5	796	3550	2845	12689	3025	13492	26.1	2.4	74.4	6.9	80.2	7.5
6	965	4304	3426	15280	3645	16257	31.8	3.0	89.6	8.3	96.8	9.0
7	1136	5067	4007	17871	4265	19022	37.4	3.5	104.9	9.7	113.3	10.5
8	1285	5731	4565	20360	4856	21658	42.3	3.9	119.4	11.1	128.9	12.0
10	1569	6998	5670	25288	6026	26876	52.3	4.9	148.7	13.8	160.4	14.9
12	1911	8523	6831	30466	7264	32397	63.6	5.9	179.3	16.7	193.5	18.0
14	2252	10044	7993	35649	8503	37923	74.9	7.0	209.9	19.5	226.6	21.1
16	2593	11565	9153	40822	9704	43280	86.2	8.0	240.5	22.3	259.8	24.1

Notes:

- The mounting structure must not flex more than $\pm 1/2$ in (± 1.2 cm) in any 10-ft (3-meter) section. 5 feet (1.5 m) of mounting structure is required above and below the antenna bays for proper pattern formation.
- Antenna radiation aperture is the distance from the center of the top bay to the center of the bottom bay. Physical space used is from the top of the top bay to the input flange at the bottom of the array, or the bottom of the bottom bay in a center-fed array. Total tower space recommended allows ten feet (3 m) of clear tower space above and below the antenna to protect from pattern interference by other antennas. At frequencies lower than 98 MHz, each of these dimensions will increase by up to 1 ft (0.3 m) per bay.
- Seven bays or less are normally end-fed. All antennas supplied with beam tilt will be center-fed. Antennas with an odd number of bays are normally not available with center feed.
- Windload and weight tabulations are estimates and assume 98 MHz. They include the bay, interbay feedline, input connection, and a fine-matching transformer. No values have been included in these tabulations for mounts. Actual values vary with the specific installation. Contact us with details of your installation if more precise values are needed.
- Antenna windloads are calculated for 112 mph (180 kph), using 50 psf (2400 N/m²) for flats and 33 psf (1600 N/m²) for rounds] per EIA standard RS-222-C and CSA standard S37-94. The surface area is calculated per EIA standard RS-222-F (C_gA).
- Deicers add approximately 1 lb (4.4 N) per bay in weight and 2 lb (8.9 N) or 0.05 ft² (0.005 m²) per bay in windload.
- Ask for technical assistance at Shively if you are planning to mount antennas on AM towers or install them at altitudes over 3,000 ft (915 m) above mean sea level.